

NA2-120MX/ NA2-240MX/ NA2-350MX/NA2-500MX

2 Zone Mixer Amplifier with USB / SD / FM / Bluetooth



Characteristics:

- 19" rack mount 2 zone mixer amplifier and built-in medial player with USB/SD/FM/ & Bluetooth;
- Rate power output at 2×120W, 2×240W, 2×350W to 2×500W;
- 2 zone separated speaker output of 100V & 8-16Ω;
- Each input with zone 1 or zone 2 output selector on front panel;
- Each zone output with volume +, volume- and mono control on front panel;
- Could be installed in two separate rooms to select different audio sources locally and adjust the local loudspeaker volume and input Bluetooth to its own room;
- Could integrate with fire alarm system or other third-party system;
- Input priority level from high to low: Mute, EMC, Mic1 and remote paging mic to others inputs;
- Each amplifier support 6 units remote microphones and 6 units remote-control panels through CAT6 cable;
- With short-circuit, clip, overload and high temp protection.

Specifications:

Model	NA2-120MX	NA2-240MX	NA2-350MX	NA2-500MX
Rated Power Output	2×120W	2×240W	2×350W	2×500W
Speaker Outputs	2 zone separated speaker output of 100V & 8-16Ω			
Connector	Line1 & EMC input: 250mV; RCA type, Mute: open circuit= remote mute, closed circuit=normal working, Two RJ45 ports for remote microphone & remote-control panel			
Input	MIC1-3: 5-8mV, 600Ω; Line, 150-470mV, 10KΩ, unbalanced RCA			
Line Out	0.775(0dBV)			
Frequency Response	60Hz-15kHz(±3dB)			
S/N Ratio	Line ≥ 85dB, Mic≥ 72dB			
THD	Less than 0.5%			
Protection	short-circuit, clip, overload and high temp protection			
Power Consumption	300W	600W	850W	1200W
Power Supply	230V AC; 50-60Hz			
Dimension	484×405×88 (WxDxH) (mm)			
Weight	6.6 kg	9.6 kg	11.9 kg	13.7 kg