

# 5 Zone Mixer Amplifier with USB/SD/FM/Bluetooth

NA5-60MX / NA5-120MX / NA5-240MX / NA5-350MX / NA5-500MX / NA5-650MX



## Characteristics:

- Tabletop 5 zone mixer amplifier with Mp3 player, FM radio & blue tooth;
- 5 zone speaker outputs 100V & single zone speaker output of 100V or 70V & 4 Ohm-8 Ohm-16 Ohm;
- Mp3 player with USB/SD input on front panel, IR remote control for Mp3 player, FM radio and Bluetooth;
- EXT Chime for closed trigger input to activate the 4-tone chime and siren;
- Mic1 priority & mute level attenuator;
- Phantom power for Mic1 & Mic 2;
- 7 Inputs includes Mic1-5 XLR inputs and Aux 1-2 inputs;
- Amp input and Pre output for external amplifier link;
- EQ of low, middle, high and master tone control;
- Complete amplifier protection includes short-circuit, clip, overload and high temp.

## Specifications:

Model	NA5-60MX	NA5-120MX	NA5-240MX	NA5-350MX	NA5-500MX	NA5-650MX
Description	5 Zone Mixer Amplifier with USB/SD/FM/Blue Tooth					
Rated Power Output	60W	120W	240W	350W	500W	650W
Speaker Outputs	100V or 70v & 4 ohm-8 ohm-16 ohm 5 Zone speaker outputs 100V					
Connector	Mic1-5 input by balanced XLR; Aux 1 RCA input, Aux 2 6.3mm phone jack input Amp input 6.3mm phone jack, Pre-Output 6.3mm phone jack EXT Chime for closed trigger input to activate the 4-tone chime and siren Mic1 Mute attenuator, Mic1-2 +48V phantom power on/off dipswitch					
Input	MIC1-5: 5-8mV, 600Ω; Aux 1-2, 150-470mV, 10KΩ					
Line Out	0.775(0dBV)					
Frequency Response	60Hz-15kHz(±3dB)					
S/N Ratio	Line ≥ 85dB, Mic≥ 72dB					
THD	< 0.5%					
Power Consumption	80W	150W	310W	450W	650W	800W
Power Supply	AC230V; 50-60Hz					
Dimension	484×350×88 (mm) (WxDxH)					
Weight	7.0 Kg	7.1Kg	8.6 Kg	8.7 Kg	8.9 Kg	9.2 Kg